

1 **OPTICAL ANTENNA SYSTEM FOR FREE-SPACE OPTICAL**
2 **COMMUNICATION SYSTEM**

3 **BACKGROUND OF THE INVENTION**

4 1. Field of the Invention

5 The present invention relates to an optical antenna system for a free-
6 space optical communication system, and more particularly to an optical antenna
7 system that has a dual laser transmission unit to perform the tasks of alignment
8 and data transmission simultaneously for a free-space optical communication
9 system.

10 2. Description of Related Art

11 The marriage of the Internet and wireless communications technology
12 has caused wireless communications technology to be the fastest growing
13 technology in recent years. The Internet consists of lots of networks including
14 local area networks (LAN) that communicate with each other. Typically, optical
15 fiber, coaxial cables or wire cables are the media used to connect two networks
16 together. However, installing the optical fiber, coaxial cables or wire cable is
17 generally time consuming and expensive.

18 Wireless communication technology can be installed more conveniently
19 than conventional media. Free-space optical (FSO) technology provides a
20 wireless communication environment with data and information transfer speed
21 equivalent to optical fiber. With reference to Figs. 4 and 5, free-space optical
22 technology can be used to link local area networks (not numbered) in a building
23 A (60) and a building B (61). Separate local area networks (LAN) or Intranets
24 are installed in building A (60) and the building B (61) to provide a medium to

1 exchanging data or information between workstations (not numbered) in the
2 buildings (60, 61). The free-space optical communication system uses an optical
3 antenna system (not numbered) to establish a communication link between the
4 two buildings (60, 61).

5 A conventional optical antenna system in accordance with the prior art
6 in a free-space optical communication system comprises a first optical antenna
7 assembly (63) and a second antenna assembly (64) that are mounted respectively
8 on the two buildings (60, 61) and correspond to each other. The first and the
9 second antenna assemblies (63, 64) connect respectively to the networks and
10 communicate with each other by means of laser beams (not shown) that transmit
11 information or data in optical signal form.

12 With further reference to Fig. 6, the first optical antenna assembly (63)
13 comprises a first optical receiver assembly (631), a first optical transmitter
14 assembly (632) and an optical alignment transmitter assembly (633). The first
15 optical receiver assembly (631) has a first optical detector (635) and a convex
16 lens (65) with a focal point (not shown). The first optical transmitter assembly
17 (632) has a first optical transmitter (636) and a convex lens (65) with a focal
18 point (not shown). The optical alignment transmitter assembly (633) has an
19 optical alignment transmitter (637) and a convex lens (65) with a focal point (not
20 shown). The first optical detector (635), the first optical transmitter (636) and the
21 optical alignment transmitter (637) are mounted respectively at the focal points
22 of the convex lenses (65).

23 With further reference to Fig. 7, the second optical antenna assembly (64)
24 comprises a second optical transmitter assembly (641), a second optical receiver

1 assembly(642) and an optical alignment receiver assembly (643). The second
2 optical transmitter assembly (641) has a second optical transmitter (645) and a
3 convex lens (65) with a focal point (not shown). The second optical receiver
4 assembly (642) has a second optical detector (646) and a convex lens (65) with a
5 focal point (not shown). The optical alignment receiver assembly (643) has an
6 optical alignment detector (647) and a convex lens (65) with a focal point (not
7 shown). The second optical transmitter (645), the second optical detector (646)
8 and the optical alignment detector (647) are mounted respectively at the focal
9 points of the convex lenses (65).

10 Since the free-space optical communication system uses laser beams for
11 data and information exchange, the first and the second optical antenna
12 assemblies (63, 64) must be aligned with each other during the data and
13 information exchange. Therefore, the optical alignment transmitter (637) in the
14 first optical antenna assembly (63) emits a laser beam (not shown) through the
15 corresponding convex lenses (65) to the optical alignment detector (647) in the
16 second optical antenna assembly (64), and the second optical antenna assembly
17 (64) aligns with the signal received from the first optical antenna assembly (63).
18 Thereafter, the laser beam emitted by the first optical transmitter (636) will be
19 efficiently received by the second optical detector (646). Likewise, the laser
20 beam emitted by the second optical transmitter (645) will be efficiently received
21 by the first optical detector (635). Consequently, a duplex data communication
22 link for the free-space communication system is established.

23 However, current optical antenna assemblies (63, 64) with a self-
24 alignment capability typically have at least three sets of optics. For example, the

first optical antenna assembly (60) contains a unique set of optics in a first optical transmitter assembly (631), a first optical receiver assembly (632) and an optical alignment transmitter assembly (633). So many elements in an optical antenna assembly will cause the optical antenna assembly to be bulky and heavy. Besides, fabrication cost of the optical antenna assembly will be generally high.

The optical alignment transmitter assembly (633) must be precisely parallel with the other optical assemblies (631, 632) in the first optical antenna assembly (63). Therefore, precise installation of the optical alignment transmitter assembly (633) and the other optical assemblies (631, 632) in the first optical antenna assembly (63) is not easy. Precise parallel alignment of the optical alignment transmitter assembly (633) and the other optical assemblies (631, 632) requires a lot of time.

To overcome the shortcomings, the present invention provides an optical antenna system for a free-space optical communication system to mitigate or obviate the aforementioned problems.

SUMMARY OF THE INVENTION

The main objective of the present invention is to provide an optical antenna system for a free-space optical communication system, which will solve the problem of parallel alignment of internal optical assemblies.

Another objective of the present invention is to provide an optical antenna system with fewer elements thereby reducing cost, weight and size of the optical antenna system.

Other objectives, advantages and novel features of the invention will become more apparent from the following detailed description when taken in

1 conjunction with the accompanying drawings.

2 **BRIEF DESCRIPTION OF THE DRAWINGS**

3 Fig. 1 is a schematic of an optical antenna system in accordance with the
4 present invention for a free-space communication system;

5 Fig. 2 is a block diagram of a fixed optical antenna assembly in the
6 optical antenna system in Fig. 1;

7 Fig. 3 is a block diagram of an adjustable optical antenna assembly in the
8 optical antenna system in Fig. 1;

9 Fig. 4 is an operational perspective view of a link in a free-space optical
10 communication system;

11 Fig. 5 is a schematic of a conventional optical antenna system in
12 accordance with the prior art for a free-space communication system;

13 Fig. 6 is a block diagram of a first optical antenna assembly in the optical
14 antenna system in Fig. 5; and

15 Fig. 7 is a block diagram of a second optical antenna assembly in the
16 optical antenna system in Fig. 5.

17 **DETAILED DESCRIPTION OF PREFERRED EMBODIMENT**

18 With reference to Fig. 1, an optical antenna system for a free-space
19 communication system in accordance with the present invention comprises a
20 fixed optical antenna assembly (10) and an adjustable optical antenna assembly
21 (20).

22 With further reference to Fig. 2, the fixed optical antenna assembly (10)
23 comprises a single wavelength optical receiver assembly (11) and a dual
24 wavelength optical transmitter assembly (12). The single wavelength optical

1 receiver assembly (11) is conventional and comprises a first convex lens (111)
2 and a single wavelength optical detector (112). The first convex lens (111) has a
3 focal point (not shown). The single wavelength optical detector (112) is mounted
4 at the focal point of the first convex lens (111) to detect optical signals (not
5 shown) and send the optical signals to a receiver amplifier (not numbered) in the
6 free-space communication system for further processing.

7 The dual wavelength optical transmitter assembly (12) comprises a
8 second convex lens (121) and a dual wavelength optical transmitter (122). The
9 second convex lens (121) has a focal point (not shown). The dual wavelength
10 optical transmitter (122) is mounted at the focal point of the second convex lens
11 (121) and is driven by a transmitter driver (not numbered) in the free-space
12 communication system. The dual wavelength optical transmitter (122)
13 simultaneously emits a first laser beam (not numbered) and a second laser beam
14 (not numbered) that have different wavelengths respectively for alignment and
15 data exchange. The first laser beam is used to align the second optical antenna
16 assembly (20) with the single wavelength optical antenna assembly (10). The
17 second laser beam is used to transmit data.

18 With reference to Fig. 3, the adjustable optical antenna assembly (20) is
19 corresponds to the fixed antenna assembly (10) and comprises a single
20 wavelength optical transmitter assembly (21) and a dual wavelength optical
21 receiver assembly (22). The single wavelength optical transmitter assembly (21)
22 is conventional and corresponds to the single wavelength optical receiver
23 assembly (11) in the fixed optical antenna assembly (10) to establish a one-
24 directional data communication link between the two single wavelength optical

1 assemblies (11, 21).

2 The optical transmitter assembly (21) comprises a third convex lens (211)
3 and an optical transmitter (212). The third convex lens (211) has a focal point
4 (not shown). The optical transmitter (212) is mounted at the focal point of the
5 third convex lens (211) and is driven by a transmitter driver (not numbered) in
6 the free-space communication system. A laser beam is produced by the optical
7 transmitter (212), passes through the third and the first convex lenses (211, 111)
8 and is received by the optical detector (112) in the single wavelength optical
9 receiver assembly (11) to create a communication link.

10 The dual wavelength optical receiver assembly (22) corresponds to the
11 dual wavelength optical transmitter assembly (12) and comprises a fourth
12 convex lens (221), an optical splitter (222), an optical alignment filter (223), an
13 optical data filter (226), an optical alignment detector (224) and an optical data
14 detector (225). The fourth convex lens (221) has a focal point (not shown), and
15 the optical splitter (222) is mounted at the focal point of the fourth convex lens
16 (221). The optical splitter (222) reflects the first laser beam and is transparent to
17 the second laser beam.

18 The optical alignment detector (224) is mounted in a position to receive
19 the reflected first laser beam and passes the received signal to an alignment
20 controller (not numbered) in the free-space communication system. The optical
21 alignment filter (223) is mounted between the optical alignment detector (224)
22 and the optical splitter (222) to filter out any reflected part of the second laser
23 beam.

24 The optical data detector (225) is mounted in a position to receive the

1 second laser beam transmitted through the optical splitter (222) and pass a
2 received signal to a receiver amplifier (not numbered) in the free-space
3 communication system. The optical data filter (226) is mounted between the
4 optical data detector (225) and the optical splitter (222) and is separated from the
5 optical alignment detector (224) by an angle of 90°.

6 Since the transmitter assemblies for optical alignment and data exchange
7 in the convention optical antenna system are merged into a single optical
8 assembly, the number of elements in the optical antenna assemblies (10, 20) are
9 reduced. Therefore, the entire optical antenna system has less volume, weight
10 and cost.

11 Since only two optical assemblies in each optical antenna assembly (10,
12 20) have to be aligned parallel, assembly of the optical antenna assemblies (10,
13 20) is easier and more convenient.

14 Even though numerous characteristics and advantages of the present
15 invention have been set forth in the foregoing description, together with details
16 of the structure and function of the invention, the disclosure is illustrative only,
17 and changes may be made in detail, especially in matters of shape, size, and
18 arrangement of parts within the principles of the invention to the full extent
19 indicated by the broad general meaning of the terms in which the appended
20 claims are expressed.